



Locked Rotor Ratings, Non-PMG 3 Phase, 60 Hz, 12 Lead, 4 Pole, 0.8 PF, 40°C Ambient							
Classic Plus Model Number	Classic Plus Marine Model Number	Trophy MDI Model Number	Locked Rotor KVA, ≤30% Transient Voltage Dip				
			60Hz				
			380V	416V	440V	460V	480V
AFD1112	N/A	N/A	13.1	16.1	17.1	18.7	20.4
AFD2112	N/A	1B4S12-MDI-2812	17.5	21.6	23.1	25.4	27.5
AFD3112	N/A	1C4S12-MDI-2823	21.6	26.8	28.4	31.1	33.8
AFD4112	N/A	1D4S12-MDI-2824	25.6	31.7	33.5	36.7	40.1
AHD5112	N/A	2E4S12-MDI-2825	35.6	43.5	48.3	52.8	60.1
AHD6112	N/A	2F4S12-MDI-2826	42.2	51.5	57.8	63.3	70.0
AHD7112	N/A	2G4S12-MDI-2837	49.9	57.5	65.3	71.6	77.9
AHD8112	N/A	2H4S12-MDI-2848	48.8	63.9	75.8	82.9	89.9
AHD9112	N/A	2J4S12-MDI-2842	53.7	70.9	83.8	91.8	100.0
BBD3112	BBD3112M	3C4S12-MDI-3610	80.9	97.5	109.7	117.3	130.7
BBD4112	BBD4112M	N/A	97.7	116.8	131.6	142.8	157.9
BBD5112	BBD5112M	3E4S12-MDI-3611	112.9	134.3	149.0	165.4	182.0
BBD6112	BBD6112M	3F4S12-MDI-3612	139	166	186	204	227
BBD7112	BBD7112M	3G4S12-MDI-3624	153	187	213	238	269
BGD3112	BGD3112M	4C4S12-MDI-3626	215	250	273	300	339
BGD4112	BGD4112M	N/A	253	322	355	401	424
BGD5112	BGD5112M	4E4S12-MDI-3637	285	343	382	414	443
BGD6112	BGD6112M	4F4S12-MDI-4312	319	398	436	491	521
BGD7112	BGD7112M	4G4S12-MDI-4314	381	467	534	585	642
BGD8112	BGD8112M	4H4S12-MDI-4316	425	556	610	676	725
BGD9112	N/A	4J4S12-MDI-4318	354	508	570	621	677
BGD10112	N/A	N/A	407	567	636	694	755
DDD3112	DDD3112M	N/A	380	474	543	620	707
DDD4112	DDD4112M	5D4S12-MDI-4322	430	516	647	722	784
DDD5112	DDD5112M	N/A	562	684	747	817	922
DDD6112	DDD6112M	5F4S12-MDI-4330	640	733	860	933	1045
EDD3112	EDD3112M	N/A	759	880	1023	1175	1327
EDD4112	EDD4112M	N/A	830	973	1137	1308	1440
EDD5112	EDD5112M	N/A	980	1180	1365	1510	1690
EDD6112	EDD6112M	N/A	1057	1260	1445	1655	1875
FDD2112	FDD2112M	N/A	Only Available as PMG				
FDD3112	FDD3112M	N/A					
FDD4112	FDD4112M	N/A					
FDD5112	FDD5112M	N/A					
FDD6112	FDD6112M	N/A					
FDD7112	FDD7112M	N/A					
GDD2112	GDD2112M	N/A	Only Available as PMG				
GDD3112	GDD3112M	N/A					
GDD4112	!""#\$%&	N/A					
GDD5112	!""#\$%&	N/A					
GDD6112	!""(\$%&	N/A					
GDD7112	!"")\$%&	N/A					

